

LEAD CUTTING/FORMING SPECIFICATIONS

(mm)

<p style="text-align: center;">● Lead configuration : CC</p> <p>∅ D = 4 to 25.4</p>	<p style="text-align: center;">● Lead configuration : MC</p> <p>∅ D = 10 to 25.4</p>
<p style="text-align: center;">● Lead configuration : RB</p> <p>∅ D = 5 to 22</p>	<p style="text-align: center;">● Lead configuration : LB</p> <p>∅ D = 5 to 22</p>
<p style="text-align: center;">● Lead configuration : RA</p> <p>∅ D = 10 to 22</p> <p>*C : 2.0±0.5 (10 to 12.5) 2.2±0.5 (16 to 22)</p>	<p style="text-align: center;">● Lead configuration : LA</p> <p>∅ D = 10 to 22</p> <p>*C : 2.0±0.5 (10 to 12.5) 2.2±0.5 (16 to 22)</p>
<p style="text-align: center;">● Lead configuration : RD</p> <p>∅ D = 10 to 12.5</p>	<p style="text-align: center;">● Lead configuration : LD</p> <p>∅ D = 10 to 12.5</p>

LEAD SPACING & RECOMMENDED PCB DIMENSIONS

(mm)

∅ D	Dimensions	∅ d	P	PC Board		Lead Configuration
				Hole diameter	Thickness	
5		0.5	2.0	0.8	1.6	CC RB/LB
6.3		0.5	2.5	0.8		
8		0.6	3.5	1.0		
10		0.6	5.0	1.0	1.6	RD/LD
12.5		0.6	5.0	1.0		CC MC
16		0.8	7.5	1.2		
18		0.8	7.5	1.2		
20		0.8	7.5	1.2		
22		1.0	10	1.2		
25.4		1.0	10	1.4		RB/LB RA/LA
		1.0	12.5	1.4		

※ Note : Other case sizes are available upon request. Please check with us about individual size and dimensions.