

LEAD CUTTING/FORMING SPECIFICATIONS

(mm)

<p>● Lead configuration : CC $\varnothing D = 3$ to 25.4</p>	<p>● Lead configuration : FC $\varnothing D = 5$ to 8</p>
<p>● Lead configuration : FM $\varnothing D = 5$ to 8</p>	<p>● Lead configuration : MC $\varnothing D = 10$ to 25.4</p>
<p>● Lead configuration : LF $\varnothing D = 10$ to 16</p>	<p>● Lead configuration : DC $\varnothing D = 22$ to 25.4</p>
<p>● Lead configuration : RB $\varnothing D = 10$ to 22</p>	<p>● Lead configuration : LB $\varnothing D = 10$ to 22</p>

LEAD SPACING & RECOMMENDED PCB DIMENSIONS

(mm)

Dimensions $\varnothing D$	$\varnothing d$	P	PC Board		Lead Configuration
			Hole diameter	Thickness	
5	0.5	5.0	0.8	1.6	CC
6.3	0.5	5.0	0.8		FC
8	0.6	5.0	1.0		FM
10	0.6	5.0	1.0	1.6	LF
12.5	0.6	5.0	1.0		
16	0.8	7.5	1.2		
18	0.8	7.5	1.2		
20	0.8	7.5	1.2		
22	0.8	10	1.2		
25.4	1.0	10	1.4		RB/LB
	1.0	12.5	1.4		
	1.0	10	2.0	1.6	

※ Note : Other case sizes are available upon request.
 Please check with us about individual size and dimensions.